

AMIC-5010

HIGHEST ACCURACY & LOWEST COST



Insulation Resistance Meter

AMIC-5010

Insulation resistance measurement - **15TΩ**:

* 50 – 1000 V, 10 V steps

* 1000 – 5000 V, 25 V steps

Memory of 999 measurement results and PC transmission.

Capacitance and DC/AC voltage measurement.

Leakage current measurement.

Digital filters function.

Measurement of protective connections and equipotential bonding.

amperis

www.amperis.com



AMPERIS PRODUCTS S.L.
Agricultura,34
27003, Lugo, Spain

Contact

+T [+34] 982 20 99 20 | F [+34] 982 20 99 11
info@amperis.com | www.amperis.com

Main characteristics are the following:

Insulation resistance measurement:

- Measurement voltage:
 - *50 – 1000 V, 10 V steps
 - *1000 – 5000 V, 25V steps
 - Continuous indication of measured insulation resistance or leakage current.
 - Automatic discharge of measured object capacitance voltage.
 - Acoustic signaling of 5 seconds intervals to facilitate capturing time characteristics.
 - Metered T_1 , T_2 and T_3 test times for measuring one or two absorption coefficients from the range of 1...600 s.
 - Adjustable measuring time to 99'59".
 - Polarization index (PI) and dielectric absorption ratio (DAR) measurement.
 - Indication of actual test voltage during measurement.
 - 1.2 mA and 3 mA test current.
 - Step voltage insulation resistance measurement (SV).
 - Dielectric Discharge calculation (DD).
 - Protection against measuring live objects.
 - Measurements with test leads up to 20 m.
- Digital filters function for measurements in high noise environment (10 s, 30 s, 60 s).**
- Continuity measurement of protective connections and equipotential bonding in accordance with EN 61557-4 with current > 200 mA.**
- Adjustable limits for measured resistance R_{ISO} and R_{CONT} .**
- Measurement of leakage current during insulation resistance testing.**
- Measurement of capacitance during the measurement of R_{ISO} .**
- DC and AC voltage measurement in the range of 0...600 V.**
- 990 cells of memory (11880 records) with the capability of wireless data transmission to a PC (with the USB-OR adapter) or through a USB cable.**
- Power supply from main power line or battery packs, low battery warning indicator, built-in fast charger.**

Measurement of capacitance

Range	Resolution	Accuracy
1...999 nF	1 nF	
1,00...49.99 μ F	0,01 μ F	$\pm(5\%m.v. + 5 digits)$

Capacity measurement result is displayed after the R_{ISO} measurement.

Medición de la tensión continua y alterna

Range	Resolution	Accuracy
0,0...29,9 V	0,1 V	$\pm(2\%m.v. + 20 digits)$
30,0...299,9 V	0,1 V	$\pm(2\%m.v. + 6 digits)$
300...600 V	1 V	$\pm(2\%m.v. + 2 digits)$

Frequency range: 45...65Hz.

"m.v." = "measured value".



AMPERIS PRODUCTS S.L.
Agricultura,34
27003, Lugo, Spain

Insulation resistance measurement

Measurement range acc. to EN 61557-2: 50 k Ω ...15,0 T Ω ($I_{ISO,nom} = 1,2 \text{ mA ó } 3 \text{ mA}$)

Range	Resolution	Accuracy
0,0...999,9k Ω	1k Ω	$\pm(3\%m.v. + 10 digits)$
1,000...9,999M Ω	0,01M Ω	
10,0...99,99M Ω	0,1M Ω	
100,0...999,M Ω	1M Ω	
1,000...9,999G Ω	0,01G Ω	
10,0...99,99G Ω	0,1G Ω	
100,0...999,G Ω	1G Ω	
1,000...9,999T Ω	0,01T Ω	
10,0...15,000T Ω	0,1T Ω	$\pm(10\%m.v. + 10 digits)$

Values of measured resistance depending on measurement voltage

Voltage U_{ISO}	Measurement range
250V	500G Ω
500V	1,00T Ω
1000V	2,00T Ω
2500V	5,00T Ω
5000V	15,00T Ω

Measurement of leakage current

Range	Resolution	Accuracy
0...1,2 mA*	Resolution and units result from the measurement range of individual insulation resistance.	Calculated basing on resistance measurements.
0...3 mA*		

* - depending on the setting.

Step voltage insulation resistance measurement

Voltaje de prueba final	Secuencia del Voltaje de prueba
1 kV	200, 400, 600, 800, 1000 V
2,5 kV	0,5, 1, 1,5, 2, 2,5 kV
5 kV	1, 2, 3, 4, 5 kV

Duration of each "step" adjustable from 30 s to 5 mins.
Measurement result for each voltage step is stored in memory.

Continuity measurement of protective connections and equipotential bonding, I=200mA

Range	Resolution	Accuracy
0,00...19,99 Ω	0,01 Ω	$\pm(2\%m.v. + 3 digits)$
20,0...199,9 Ω	0,1 Ω	
200...999 Ω	1 Ω	

Voltage on open terminals: 4...24 V.
Output current at R > 15 Ω : min. 200 mA ($I_{sc} : 200...250 \text{ mA}$).
Compensation of test lead resistance.
Current flowing in both directions, mean value of resistance is displayed.

Contact

+T [+34] 982 20 99 20 | F [+34] 982 20 99 11
info@amperis.com | www.amperis.com

Specifications AMIC-5010

Electric security:

Type of insulation	Double, acc. to EN 61010-1 and IEC 61557
Measurement category	CAT IV 600V (III 1000V) EN 61010-1
Above sea level	3000 m.
Protection class acc. to EN 60529	IP54 (IP67 with cover closed)

Other technical data:

Power supply	90 – 265V 50/60Hz and built-in battery packs
Weight	aprox. 7 kg
Dimensions	390 x 310 x 170 mm
Display	LCD
Measurement results memory	990 cells of memory (11880 records)
Transmission of measurement results	USB or wireless interface

Standard accesories:

USB cable
Test lead banana plug; 1,8 m; 10kv; red
Test lead banana plug; 1,8 m; 10 kv; blue
Test lead banana plug; 1,8 m; 10 kv; black; shielded
"Crocodile" clip 5,5 kv; black
"Crocodile" clip 5,5 kv; blue
"Crocodile" clip 5,5 kv; red
Pin probe 5,5 kv with banana connector; red
Pin probe 5,5 kv with banana connector; black
Carrying case L4 for accesories
Power cord
Battery pack (built-in)
Software
Calibration certificate

Optional accesories:

Test lead banana plug; 3 m; 10kv; red
Test lead banana plug; 3 m; 10kv; blue
Test lead banana plug; 3 m; 10kv; black; shielded
Test lead banana plug; 5 m; 10kv; red
Test lead banana plug; 5 m; 10kv; blue
Test lead banana plug; 5 m; 10kv; black; shielded
Test lead banana plug; 10 m; 10kv; red
Test lead banana plug; 10 m; 10kv; blue
Test lead banana plug; 10 m; 10kv; black; shielded
Test lead banana plug; 20 m; 10kv; red
Test lead banana plug; 20 m; 10kv; blue
Test lead banana plug; 20 m; 10kv; black; shielded
Carring backpack L-7
OR-1 radio receiver for data transmission



Receiver – interface for radio transmission OR1 (USB).



AMPERIS PRODUCTS S.L.
Agricultura,34
27003, Lugo, Spain

Contact

+T [+34] 982 20 99 20 | F [+34] 982 20 99 11
info@amperis.com | www.amperis.com